

New Feature! Never Lose Code!

☆ 、 Programming your Remote

1. Manually turn on the TV.
2. Press and hold the SET-UP key until the LED blinks and remains on, then release the button.
3. Find your 3-digit code from the code table and enter it. After the code is entered the indicator light will turn off and you are done.

NOTE: If the LED blinked rapidly when you entered the code you may have entered an invalid code; recheck the code list and try again. Also if volume and channel functions do not work then you do not have an exact code match and please try another code.

4. Enter your code here for reference

To return to Factory Setting (Pre-programmed for a specific brand)

1. Press SETUP and hold until LED stays on.
2. Press CC.

☆ 、 Programming your Remote using code search.

If the code for your TV is not listed or you cannot get the TV to respond try the following:

1. Turn on the TV.
2. Press and hold the SET-UP key until the LED blinks and remains on, then release the button.
3. Press the channel [CH+] up button slowly over and over again (60 or more times) until the channel changes. The LED will blink and then stay lit. If you bypass the code just press CH- key to go backward through the library until the TV changes channels. Pressing CH+ changes direction to forward again.
4. Now press ENTER to lock in the code.



☆、 Setup Codes for TV

Code list:

Brand	Code
Admiral	500,501,610,614,615,902
Advent	911,932,933
Aiko	900
Akai	601,903,922
AOC	103,601,617
Apex	000,604,618
Audiovox	100,101,900,901
Belcor	617
Bell&Howell	611,620
Bradford	901
Brockwood	617
Broksonic	614,902
Candle	601,619
Celebrity	605
Changhong	618
Citizen	601,619,900,903
Clairtone	103
Concerto	619
Contec	103,901
Craig	901
Crosley	301,303
Crown	901
Curtis Mathes	100,102,301,400,401,402,405,500,603 606,611,619,620,621,903
CXC	901
Daewoo	100,101,617,900
Daytron	617
Dumont	617,700
Durabrand	201,614,615,901,902,914,918
Electroband	103,605
Emerson	101,103,200,201,602,607,614,615,617 620,901,902
Envision	601
ESA	201,601,901,903
Fisher	620,801
Fujitsu	300,615
Funai	201,615,901
Futuretec	901
GE	100,200,202,400,401,402,405,607,608 802
Gibraltar	601,617,700
GoldStar	601,607,617,619
Grundig	615,901
Haier	914,918
Hallmark	607
Harvard	901
Hitachi	005,606,611,916,619
ILO	921,925
Infinity	301
Inteq	700
Insignia	201,301,303,614,909,919,920,934
JBL	000,301,604,618
JCB	605
JC Penny	202,400,402,405,601,607,608,609,617 800,903
JVC	701
KEC	901
Kenwood	601,617
KLH	618
KTV	103,601,901
Konka	001,002,003,304,904
LG	619,700,910
Logik	611
Luxman	619
LXI	301,400,402,607,609,620
Magnavox	301,302,303,601,615,617,803,905,906 907,908,909
Majestic	611
Marantz	301,601
Matsushita	004
Megatron	606,607

Brand	Code
MEI	103
Memorex	004,104,607,611,614,615,620
MGA	104,500,601,607,617
Minutaz	608
Mitsubishi	104,500,601,607,617
Motorola	500,802
MTC	103,601,617,619,903
Multitech	901
NAD	603,607,609
NEC	601,617,619
Nikko	601,607,900
Noshi	800
NTC	900
Olevia	923
Onwa	901
Optimus	004,603,620
Optonica	500,610
Orion	614,615,902
Panasonic	004,202,610,802
Philco	301,601,606,614,617
Philips	301,302,303,601,615,617,803,905,906 907,908,909
Pilot	601,617
Pioneer	600,603
Polaroid	400,910,913,915,917,920
Portland	617,900
Prism	202
Proscan	400,402
Proton	102,607
Pulsar	617,700
Quasar	004,202,610,802
RadioShack	400,402,607,610,617,619,620,621,901
Realistic	601,607,610,617,619,620,901
RCA	400,401,402,403,404,405,600,612,617 623,800
Rhapsody	103
Roomconx	614,615,902,924
Runco	601,616,700
Sampo	601
Samsung	601,607,617,619,903,930
Sansui	614,615,902
Sanyo	620,801,931
Scotch	607
Scott	607,615,617,901,902
Sears	201,301,400,402,607,609,615,620,622 801
Sharp	500,501,610,929
Sharp(LCD)	912,929
Shogun	617
Signature	611
Simpson	803
Sony	605
Soundesign	607,615,901
Squareview	201
SSS	617,901
Starlite	901
Supreme	605
Sylvania	201,301,601,901
Symphonic	201,901
Tandy	500
Tatung	802
Technics	004,202
Techwood	202,619
Teknika	104,301,605,611,615,617,619,900,901
TMK	602,607,619
Toshiba	609,613,620,903
Trutech	101
Victor	701
Vidtech	607,617
Vizio	927
Wards	301,601,607,608,610,611,615,617,619 926,928
Westinghouse	101,605,614
White Westinghouse	601,617
Yamaha	611,614,619,700,900
Zenith	611,614,619,700,900