

ARTECK™

User Manual

Arteck HB030B Bluetooth® Keyboard



Welcome

Thank you for choosing this Artek HB030B wireless keyboard. To ensure optimum performance and safety, please read these instructions carefully before operating this product. It is strongly recommended you keep the manual for future reference.

Statement

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by ARTECK is under license. Other trademarks and trade names are those of their respective owners.

“Windows” is a trademarks of Microsoft Corporation in the United States and/or other countries.

“Android” is a trademark of Google Inc.

Product Specifications

1. Standard Micro USB interface
2. Operating distance up to 10 meters
3. Modulation system: GFSK
4. Operation voltage: 3.0-4.2V
5. Operating current: <2.5mA
- 6 . Standby current: <0.3mA
7. Sleep current: <40uA
8. Charge current: ≥ 200mA
9. Standby time: >200 days
10. Charge time: <2 hours
11. Lithium battery capacity: 500mA
12. Uninterrupted working time: >90 hours

- 13. Lithium battery life: 3 years
- 14. Lithium battery specification: 3.8*20*35mm
- 15. Keying force: 60±10g
- 16. Keying life: 3 million strokes
- 17. Operating temperature: -10 - +55°

Package Contents:

Arteck HB030B Wireless Keyboard *1
Micro USB charging cable *1
User manual *1

Getting Started Guide

1. Button



On/Off Slide Switch: Slide switch ON or OFF to control the device power turn on or turn off.



Bluetooth Connect Button: The ON/OFF switch is already in the ON position, Press on the [Connect] button, the keyboard is now ready to be connected to your device.

2. Status Light



CAPS Status Light: Press on the [Caps Lock] button, the Caps Lock function will be on, and the Caps Lock Status will be illuminated. Sometimes the light will not be on but function is valid for some Android system.



Bluetooth Status Light: Press on the [Connect] button, the [Status] light will be blink blue, indicator light will stay on until the keyboard connect with your device.
























Chare Light(red): Turn on when charging, turn off when fully charged.



Battery Status Light: Slide the power button on. The blue light will illuminate for 4 seconds and then turn off to save power. Your keyboard is still on. The power light will be blinking at low battery.

3. Function Keys

	Home		Virtual Keyboard		Select All
	Copy		Paste		Android/Windows Mail
	Search		Switching Language		Previous Track
	Play / Pause		Next Track		Volume down
	Volume up		Sleep / Wake		Light On / Enhanced Light / Light Off
	Switch Backlit Colors		Switch Backlit Colors		Move the cursor to the top
	Move the cursor to the bottom		Move the cursor to the beginning		Move the cursor to the end

iOS System

	Select All		Copy		Paste
	Cut	control+spacebar	iOS 9: Switching Language	command+spacebar	iOS 9 Earlier: Switching Language

Android System / Windows System

Ctrl+A	Select All	Ctrl+C	Copy	Ctrl+V	Paste
Ctrl+X	Cut	control+spacebar	Switching Language		

Note: In Windows system, press F1-F12 to have F1-F12 function, press Fn+F1 to F12, the function will be the function showed on the icon. For example, Fn+F1 (Virtual Keyboard), Fn+F2 (Select All), Fn+F3 (Copy), Fn+F4 (Paste), Fn+F5 (Mail), Fn+F6 (Search), Fn+F7 (Switch Language), Fn+F8 (Previous Track), Fn+F9 (Play/Pause), Fn+F10 (Next Track), Fn+F11 (Volume Down), Fn+F12 (Volume Up).

Steps of Pairing the Keyboard with Your Device

- Step 1: On the keyboard, slide the power button on. The blue power light will illuminate for 4 seconds and then turn off to save power. Your keyboard is still on.
- Step 2: Press the [Connect] button, the status indicator will be blinking blue.
- Step 3: On your device, select: Setting - Bluetooth - On.
- Step 4: Your device will display "Bluetooth keyboard 3.0" as an available device.
- Step 5: Select "bluetooth keyboard 3.0" on your device, the keyboard is paired to your device now.
- Step 6: Press Fn+Q if your device is iOS; press Fn+W if your device is Android; press Fn+E if your device is Windows.

Notice:

If you didn't finish the step 6, some Windows system or Android system might cannot use the keyboard properly. In this situation, you might disconnect keyboard and click "Forget This Device" in the bluetooth list and connect this keyboard following step 1-6 again.

Fn+Function Keys Notice

Provide shortcuts to useful functions, first press and hold the Fn Key; second, press the function key you want to use.

Backlight with colorful keyboard guide

1. Press the Fn+ [💡] light key one time to turn on the backlit, press the second time to enhance the backlit, press the third time to turn off the backlit.
2. Press Fn+[💡]+PgUp or press Fn+[💡]+PgDn to switch the backlit colors. This keyboard has 7 colors available to choose.

Charge the battery

Turn on the Bluetooth keyboard.

The Power indicator light (blue) will illuminate for 4 seconds and then turn off to save power. Your keyboard is still on.

If the power indicator light keep blinking, it means the battery is low, you need to charge the keyboard with below steps:

1. Plug the Micro USB charging cable into the keyboard.
2. Plug the USB plug on a computer or USB power adaptor.
3. Charge for 1-3 hours, or until the charge light is turned off.

ⓘ Caution:

1. When not in use for a prolonged period, it is recommended that you turn off the keyboard to lengthen battery life.
2. When the power status light flash, it is recommended that charging the keyboard not less than 2 hours.

Energy-saving sleep mode

Keyboard's long life battery lasts for several months of normal use. The keyboard will go into sleep mode if left on and not being used; press any key and wait a second or two to bring it out of sleep mode.

Safety Caution

1. Keep the item away from sharp objects.
2. Do not place heavy object on the keyboard.
3. Away from microwave items.
4. Do not force or distorted the keyboard.
5. Keep away from oil, chemical or other organic liquid.

Cleaning

Clean the keyboard with water, alcohol or alcohol based disinfectant.

Troubleshooting

1. Make sure the keyboard is on (slide switch in "ON" position).
2. Make sure the keyboard is in operating distance (within 10 meters).
3. Ensure the battery storage has power.
4. Make sure the Bluetooth in tablet / PC / smartphone is on.
5. Ensure wireless keyboard have already match with bluetooth.

Disposal of Waste batteries

Insert screwdriver between plastic top and metal case at keyboard top or bottom and Pry up plastic top and remove it completely. This action destroys keyboard separate battery from circuit board, it is your responsible to hand this over to an applicable collection and recycling will help to conserve natural resources and prevent potential negative consequences for human health and the environment due to the possible presence of hazardous in batteries and electrical and electronic equipment.

Warranty

Our company provides customers with a warranty of **24 months** from the date of purchase.

Contact Us

For any inquires or comments concerning our products, please send an email to support@iarteck.com, and we will respond to you as soon as possible. If there is any quality-related issue with the product, you may request a replacement or refund by submitting a request to support@iarteck.com.