

Dear user

Thank you for choosing **REDRAGON** Brand, to protect your rights and for better customer service, we ask that you note our warranty rules.

1. Within warranty period, repair is guaranteed for failure due to electrical circuit problems. Man-made damages, such as disassembly, hard impacts, submersion into water, plugging into improper current or voltage, and damage caused by natural disasters such as fire, flood, or earthquake are not included.
2. Consumable parts (such as foot stick) and spare parts replacement are not included in our warranty.
3. Please fill out the warranty card. Warranty card is valid with the stamp of the retailer.
4. This warranty card will not be reissued if lost. Please keep it in a safe place.

1

OS support

Windows XP/Vista/Win7/Win8/Win10

How to connect the keyboard with a computer**Wired Connection**

Slide the ON/OFF switch on left side of the keyboard to OFF.

Take out the USB A to USB Type C cable in the package and connect the keyboard with your computer. Press FN+5(USB) key, the LED marked with M twinkle in 5 times indicated the connecting successful.

The computer will recognize and configure the keyboard automatically.

Once the keyboard is powered up, charging begins. The LED marked with M lights on red. It will turn to white when keyboard is fully recharged.

2.4G Wireless Connection

1. Slide the ON/OFF switch on left side of keyboard to ON.

2. Press FN+[4] for about 3 seconds, the LED marked with M flashes quickly in green, plug the USB receiver into any available USB port on your computer within 20 seconds. The computer will recognize and configure the keyboard automatically.

3. The indicator will flash on Red when the battery is low. Please recharge the keyboard in time by plug type C cable into computer or it will turn off automatically soon. Please note LED marked with M will be light on Red while charging, it turn to Green when charging completed (In 2.4g connecting mode).

2

Macro recording function

There are 4 profiles keys from M1 to M4, each profile can assign with 5 macro keys from G1 to G5, total 20 group macro recording.

1. Press M key (M1/M2/M3/M4) to set a profile group, the key lights ON.
2. Press MR key (MR key lights ON), then press G key (G1/G2/G3/G4/G5), the key lights ON.
3. Record the desired keys.
4. Press MR key to complete recording (MR key lights OFF).

For example: M1 → MR → G1 → ABC → MR

How to play Macro

1. Choose the profile group by press M key from M1 to M4.
2. Press the Macro key from G1 to G5.

For example: M1 → G1(ABC).

How to delete Macro

1. Choose the profile group by press M key from M1 to M4 (The key backlighting in flash).
2. Press MR key (MR key backlighting in flash).
3. Double press G keys from G1 to G5 (The key lights OFF).
4. Press MR key to save (MR key lights OFF).

How to recharge the keyboard

Find the USB A to USB type C cable in the packaging, plug the keyboard and connect it with computer for charging, the LED indicator (M) of keyboard will be turn to red. Remark: The LED indicator (M) will turn to red when keyboard is out of battery.

5

Swap functions of [W][A][S][D] and arrow keys

1. Press and hold the [FN] key, and then press the [W] key to interchange the function of the four letter keys [W][A][S][D] and the four arrow keys [↑][↓][←][→].
2. Repeat the above operation to resume the previous setting.

FAQ

1. If the keyboard doesn't respond, please check if the keyboard's USB cable is correctly inserted into the corresponding USB port on the computer, or try another USB port on the computer.
2. If you spill liquid on the keyboard, please remove the keyboard's USB cable from the computer immediately. Wipe up excess liquid and put the keyboard in a warm place (for instance, under a lamp) to let the keyboard dry naturally before using again.



6

Bluetooth Connection

1. Slide the ON/OFF switch on left side of keyboard to ON.
2. Press FN+[1] or [2] or [3] for other Bluetooth devices, the LED marked with M flashes in blue (or cyan/magenta for the others).
3. Turn on Bluetooth and scan for available devices on your computer or smart phone. It will find "BT3.0Keyboard" or "BT5.0 KB" device. Select one of them to get connected with it automatically.
4. The indicator will flash in Red when the battery is low. Please recharge the keyboard in time by plug type C cable into computer or it will turn off automatically soon. Please note LED marked with M will be light on Red while charging, it turn to cyan/magenta when charging completed (In Bluetooth connecting mode).

Function Introduction

1. With standard USB and 2.4G/BT connections, the keyboard can be used on computers without any software or driver installation.
2. There are 20 backlight effects.
3. Commands of key combinations with [FN] key.
 - [FN]+[Ins]: Change backlight mode. There are 20 backlight effects.
 - [FN]+[Del]: Change back light color.
 - [FN]+[←]: Slow down the running speed of backlight.
 - [FN]+[→]: Add up the running speed of backlight.
 - [FN]+[TAB]: Turn the backlight to white.
 - [FN]+[Win]: Disable or enable the [Win] key.
 - [FN]+[W]: Switch the original W/A/S/D to arrow keys and right arrow keys to W/A/S/D, press again to restore.
 - [FN]+[1]: Select Bluetooth device one (for Bluetooth connection).

3

- [FN]+[2]: Select Bluetooth device two (for Bluetooth connection).
- [FN]+[3]: Select Bluetooth device three (for Bluetooth connection).
- [FN]+[4]: Change to 2.4G wireless connection. Press and hold the [FN]+[4] for 3 seconds to pair the keyboard with its receiver.
- [FN]+[5]: Switch to Wired connection.
- [FN]+[ESC]: Set the keyboard to default setting.

Scroll button function

Scroll button is located on the right corner of the keyboard for volume adjustment and keyboard backlight brightness adjustment function.
 Backlight brightness adjustment: Press key, it is light on White color, scroll button can switch in different brightness level.
 Volume adjustment: Press key the key light's OFF, scroll button can be used to switch the volume level.

Multimedia function on F9-F12

- FN+9: Browser
- FN+10: Research
- FN+11: Calculator
- FN+12: E-mail

Shortcut key function

- Previous track
- Next track
- Play / Pause

4



REDRAGON
HORUS
 WIRED / 2.4G / BT MECHANICAL GAMING KEYBOARD



Please scan here to
 download user manual

Wired / 2.4 / BT Mechanical Gaming Keyboard
 Operating Instructions

7